How to install Billing Cashier and Client.

- 1.Download the installer from e2Links website: http://www.e2links.com.my
- 2. First install the Billing at Cashier. Just simply click "Next" until "Finish",

After install completed click the icon below to open your cashier.

e2links Cybercafe Setting
Server Config
Administrator Account: 0 Cybercafe ID:
Main Center Address: 103.246.217.55 Port: 8080 Check
Netbar Info.
Name: TEMP
Bar Setting
Billing ID: 1 MAC Address: 002185C4AB3E
Emergency Mode Setting © Enable Prohibited
Enable With Management Passwrod
Enable Without Management Passwrod
Management
Password:
Check Out All OK CANCEL

3.Now Login to e2Links Manage:

http://manage.e2links.com.my

Manage
Carine
54
Reset

4.Go to "Store Settings"

Ś	M-Plus	2		Ø.
	1 Store Setting	Stores Setting	Cancel Membership	Offline Refund
	Operation Gurey			
-	Financial Management			
	Inventory Management			

5.Go to Wizard and fill the Server Config.

	Return to Home	Wizard	Cybercafe Setting
*	Wizard	* * * * * * * *	Server Config
-	Basic Config	1.Basic Config	Administrator Account: Cybercafe ID:
	Operator		Main Center 199 726 217 57 Dath 8080 Check
-	Bar Info	Cybercafe Administrator account:	Address: Pole occurrent Pole occurrent
*	Level Config	CyberCafe ID: 1D1DB	Netbar Info.
-	PC Info	Billing Mode: Based On Amount 💌	Name: 0
	Price	Free Time: 180 Seconds	C Bar Setting
45	Topup Freebies	Roaming with Free Account: O Yes O No	Biling ID: 1 MAC Address: 002185C4AB3E
•	Package O	Bounding: Round down to 50 Cents	
F 1 182	llinks Soft	I oral server IP	Emergency Mode Setting
E.	58M		C Enable Prohibited
U N		нер	C Enable With Management Passwrod
			Enable Without Management Passwrod
			Management Password:
			Check Out All OK CANCEL
		Mada	e2links
		NAX >>	

6.After Fill the Server Config, you need to add	d cashier MAC address to "Bar Info"
	Change Carter

Return to Home	TEMPCashier Counter Setting Cybercafe Setting
Return to Home Exist Basic Config Barinfo Event Config Price Frice Fackage Package Soft Soft Soft	TXIPCasher Counter Setting X Cybercafs Bar D Bar D Bar Name Machinetrature Cybercafs Esting Server Config Cybercafs D: Machinetrature Cybercafs D: Name: 0 D Bar Setting 1 Emergency Mode Setting Cybercafs D: Enable Wethout Management Passwood 4 Machinetrature Cybercafs D: Bar Itane: [TEST] Strint Save 1: Cybercafs D:
	Save it.

7.Click "OK" and Finish.

8.After that go to "PC Info", Add PC before install e2links Client.

1	Retur	n to Home	
*	Wizard	i	
*	Basic	Config	
*	Operat	tor	
*	Bar Ir	1fo	
*	Leve1	Config	
23	PC Ini	fo 1	8
Area	a Config		
C PC	Info	2	
B	Price		
*	Topup	Freebies	8
*	Packag	ge	8
		GO	
- *E2	links Sof	ft	

9.																		
TEMP	PC Info (PC I	Informat	tion may chan	ge, please	go check at Cas	hier C	ounter!)											
Area:	All 💌 PC Na	ame:	IP:		Search													
	Cybercafe	PC No	P Address	PC Area	MAC Address	CPU	Radiotor	Motherboard	Graphic Card	RAM	Harddisk	Monitor	Power Supply	Casing	Keyboard	Mouse	Webcam	Earphone
																		(m) t
																		\$1%b +
		r																
	Add	Delete	Batch Addin	g PC					TotalOre	ecords T	'his page0re	cords Per	Page 12 reco	rds The fir	st 1 Pa	ige Go	<< Previou	s Next >>

TEMPBatc	h Adding PC	2				
Area*:	A 💌 Number Of PCs*:	PC	The First PC's Name*:	Example:A001,YX002 and etc	Start IP*:	
CPU:			Motherboard:		Graphics:	
Memory:			Hard Disk:		Power:	
Chassis:			Monitor:		Keyboard:	
Mouse:			Camera:		Headphone:	
			197	Save		

10.After added all the PC, you need Login to cashier and synchronize all the PC list to Cashier.

Note:Use administrator account to login.

Sign In	X
Webar	Management Platform
Operator	✓ Language
Password	
Options	Sign In

Cashier(C) User Manag					
	gement(<u>D</u>) Reci	ords(Q) Settin	igs(<u>S)</u> Tools(<u>T</u>) He	lp(H)	
(A) (C)			Cybercafe	Polla.	A Contraction
On/Off Duty Refresh	(F1) New Use	er(F2)	Client Cybe	ercafe Id Card(F5)	Change Password(F7
hortcut:			Window layout (V)	•	✓ M-Plus Nev
1	F	PC	Change Skin(E)	Level	Start Time
Jser Info.	•			_	
Cybercafe Setting Server Config Administrator Account:	c	ybercafe ID:		e2l Center Config	nks Cashier uration Check Success!
Main Center Address:	103.246.217.55		Port: 8080	1 Check	
Netbar Info.		1 1 // 01	3.11		
Netbar Info.	C	lick "Che	ck" to synchron	nize data.	
Netbar Info. Name: TEMP	C	lick "Che	ck" to synchron	nize data.	
○ Netbar Info. Name: TEMP ○ Bar Setting Billing ID: 1	С М	Click "Che AC Address: 002	ck" to synchron 185C4AB3E	nize data.	
Netbar Info. Name: TEMP Bar Setting Billing ID: 1 Emergency Mode Setting Emergency Mode Setting	(M nable Prohibited nable With Manager	Click "Chee AC Address: 002	ck" to synchron 185C4AB3E	nize data.	
Netbar Info. Name: TEMP Bar Setting Billing ID: 1 Emergency Mode Setting Emergency Mode Setting Emergency Mode Setting Emergency Mode Setting	(mable Prohibited inable With Managen inable Without Mana	Click "Cher AC Address: 002 nent Passwrod gement Passwrod	ck" to synchron	nize data.	
Netbar Info. Name: TEMP Bar Setting Billing ID: 1 Emergency Mode Setting Emergency Mode Setting Emergency Mode Setting Emergency Mode Setting	(M nable Prohibited inable With Manager inable Without Mana	Click "Chee AC Address: 002 nent Passwrod gement Passwrod	ck" to synchron	nize data.	
Netbar Info. Name: TEMP Bar Setting Billing ID: 1 Emergency Mode Setting Emergency Mode Setting Emergency Mode Setting Emergency Mode Setting Emergency Mode Setting	(mable Prohibited inable With Manager inable Without Manager	Check "Check AC Address: 002	ck" to synchron	nize data.	
Netbar Info. Name: TEMP Bar Setting Billing ID: 1 Emergency Mode Setting Emergency Mode Set	(mable Prohibited inable With Manager inable Without Mana	Click "Cher AC Address: 002	ck" to synchron 185C4AB3E	οκ CANC	

11.Go to "Settings" >"Cybercafe" and click "Check" to synchronize.

12.After synchronize success, you can now install e2Links Client.

Go to client PC,open the installer that you download from e2Links website, Just simply click "Next" and input the cashier IP,and then click "Next" to install.

Which PC are you ins	talling e2lir	uks Billing Sy	rstem?	U
Input Local Server	Input yo	ur cashier IP	address.	
21 inks Billing System —				